



Bluetooth[®] mesh SDK 2.1.0.0 GA

Gecko SDK Suite 3.2

June 16, 2021

Bluetooth mesh is a new topology available for Bluetooth Low Energy (LE) devices that enables many-to-many (m:m) communication. It's optimized for creating large-scale device networks, and is ideally suited for building automation, sensor networks, and asset tracking. Our software and SDK for Bluetooth development supports Bluetooth Mesh and Bluetooth 5.2 functionality. Developers can add mesh networking communication to LE devices such as connected lights, home automation, and asset tracking systems. The software also supports Bluetooth beaconing, beacon scanning, and GATT connections so Bluetooth mesh can connect to smart phones, tablets, and other Bluetooth LE devices.

These release notes cover SDK versions:

2.1.0.0 released June 16, 2021



KEY FEATURES

- Integration with Secure Vault
- Addition of HSL models
- Support for dynamic GATT database
- Support for updated compiler versions

Compatibility and Use Notices

For more information about security updates and notices, see the Security chapter of the Gecko Platform Release notes installed with this SDK or on the [Silicon Labs Release Notes page](#). Silicon Labs also strongly recommends that you subscribe to Security Advisories for up-to-date information. For instructions, or if you are new to the Silicon Labs Bluetooth mesh SDK, see [Using This Release](#).

Compatible Compilers:

IAR Embedded Workbench for ARM (IAR-EWARM) version 8.50.9

- Using wine to build with the IarBuild.exe command line utility or IAR Embedded Workbench GUI on macOS or Linux could result in incorrect files being used due to collisions in wine's hashing algorithm for generating short file names.
- Customers on macOS or Linux are advised not to build with IAR outside of Simplicity Studio. Customers who do should carefully verify that the correct files are being used.

GCC (The GNU Compiler Collection) version 10.2.0, provided with Simplicity Studio.

Link-time optimization feature of GCC has been disabled, resulting in slight increase of image size

Contents

- 1 New Items2
 - 1.1 New Features.....2
 - 1.2 New APIs.....2
- 2 Improvements.....3
 - 2.1 Changed APIs.....3
- 3 Fixed Issues4
- 4 Known Issues in the Current Release5
- 5 Deprecated Items6
- 6 Removed Items7
- 7 Using This Release8
 - 7.1 Installation and Use.....8
 - 7.2 Security Information8
 - 7.3 Support.....9

1 New Items

1.1 New Features

Added in release 2.1.0.0

Secure Vault Integration

Beginning with release 2.1.0.0, the Bluetooth Mesh SDK uses the Secure Vault Key Management functionality for storing mesh cryptographic keys when Secure Vault High devices are used.

The Secure Vault integration is visible to the customer in a number of ways on Series 2 devices:

- The layout of NVM3 data for cryptographic keys and their related metadata changes. Key migration functionality is provided for projects that have been created using SDK versions 2.0 or earlier. A one-time key migration needs to be done when the firmware on a device is updated.
- Key data visibility is intentionally limited on regular mesh nodes. An application on a regular mesh node is not permitted to view application or device key data using the `sl_btmesh_node_get_key()` BGAPI command, while an application on an embedded Provisioner node is allowed to do so.

For further information on key storage in Secure Vault please refer to [AN1271: Secure Key Storage](#).

Compiler Support

Supported compilers have been updated to GCC version 10.2.0 and IAR version 8.50.9.

New Example Applications

HSL Lighting example (**Bluetooth Mesh - SoC HSL Light**) was added to demonstrate a light node that is controllable over HSL server models.

IOP demos (**Bluetooth Mesh - IOP Test - ***) were added for the Radio boards in the Pro Development Kits (SLWRB4104A, SLWRB4181A, SLWRB4181B, SLWRB4182A). The demos allow testing interoperability with mobile phones. The test requires four examples, each example representing one of the Mesh features: proxy, relay, friend, and LPN.

New Components

- HSL Server Component was added.
- Support for dynamic GATT database (a Bluetooth LE feature) was added.

1.2 New APIs

Added in release 2.1.0.0

Because of Secure Vault integration, the details of storing encryption keys and their related metadata has changed on Series 2 devices. A new BGAPI class for migrating encryption keys and the embedded Provisioner's device database after a firmware update on Series 2 devices has therefore been added. It has the following commands:

- `sl_btmesh_migration_migrate_keys`
- `sl_btmesh_migration_migrate_ddb`

2 Improvements

2.1 Changed APIs

Changed in release 2.1.0.0

The following BGAPI commands in the prov class now return after parameter validation, and the actual requested operation takes place after a BGAPI response is given. The completion of the requested operation is signalled by a corresponding BGAPI event:

- **sl_btmesh_prov_add_ddb_entry()** – completion of addition is signalled by sl_btmesh_evt_prov_add_ddb_entry_complete
- **sl_btmesh_prov_delete_ddb_entry()** – completion of deletion is signalled by sl_btmesh_evt_prov_delete_ddb_entry_complete

The following BGAPI command in the prov class has an additional event that may be generated after it is called:

sl_btmesh_prov_init – in addition to sl_btmesh_evt_prov_initialized, sl_btmesh_evt_prov_initialization_failed may be generated.

A BGAPI command has been added to the generic client model BGAPI:

mesh_generic_client_init_hsl()

A BGAPI command has been added to the generic server model BGAPI:

mesh_generic_server_init_hsl()

3 Fixed Issues

Fixed in release 2.1.0.0

ID #	Description
3878	Application should ignore GATT events for Mesh characteristics
342521	Math library does not grow the size of the image unnecessarily
358019	Corrected result code given when model publication with friendship credentials is requested but friendship is not supported
404070	Corrected result code given when provisioner command to create a network key is called on a non-provisioner device
454332	The LE GAP API should be used for device local name advertising
464907	Removed unnecessary 'heartbeat started' BGAPI event when configuration client disables heartbeat on a node
653405	Out-of-the-box switch sample application current consumption is now at the expected level
654477	DCD correctly decoded by Network Analyzer
660048	Button Press UC component doesn't require IO Stream component unnecessarily
687105	BT Mesh Commands work with NCP Target example and NCP Commander
690803	Fixed duplicate vendor model IDs in code generator
690862	SoC empty example now starts beaconing on xG22 hardware
707497	Corrected PSA cryptographic context allocation
707524	Fixed a regression with IV recovery guard timer, not allowing another recovery too soon
710381	Fixed lighting default state handling when a non-default range for the corresponding model was set
711359	Fixed parameter checking for provisioning session creation BGAPI call

4 Known Issues in the Current Release

Issues in bold were added since the previous release.

ID #	Description	Workaround
401550	No BGAPI event for segmented message handling failure	Application needs to deduce failure from timeout / lack of application layer response
418636	Issues with mesh_test local configuration state API (node identity, relay, network retransmission)	
454059	A large number of key refresh state change events are generated at the end of KR process, and that may flood NCP queue	Increase NCP queue length in the project
454061	Slight performance degradation compared to 1.5 in round-trip latency tests was observed	
624514	Issue with re-establishing connectable advertising if all connections have been active and GATT proxy is in use	Allocate one more connection than is needed
650825	Issue with retransmissions when a model is publishing periodically	Set up retransmissions in the model state and trigger periodic publishing by an application timer
676798	Automatic LPN polling may miss friendship termination deadline due to oscillator inaccuracy	Ensure application timer-based explicit polling takes place before friendship terminates, if the timeout for friendship termination is long
683518	Friendship termination event is not immediately seen when a friendship clear message is received	The event will be raised once friendship timeout expires
692961	At high load, NCP firmware may run out of buffers in such a way that it does not automatically recover	If high load situations are expected, allocate enough memory for buffering in Bluetooth project settings.
713152	Limited precision of calculation causes rounding errors in the binding between Light Lightness Actual and Light Lightness Linear	Use Light Lightness Actual whenever possible

5 Deprecated Items

The following BGAPI command in the node class has been deprecated:

`sl_btmesh_node_erase_mesh_nvnm()` – use `sl_btmesh_node_reset()` instead.

6 Removed Items

None

7 Using This Release

This release contains the following

- Silicon Labs Bluetooth mesh stack library
- Bluetooth sample applications

If you are a first time user, see *QSG176: Silicon Labs Bluetooth Mesh SDK v2.x Quick-Start Guide*.

7.1 Installation and Use

A registered account at Silicon Labs is required in order to download the Silicon Labs Bluetooth SDK. You can register at https://siliconlabs.force.com/apex/SL_CommunitiesSelfReg?form=short.

Stack installation instruction are covered in *QSG176: Silicon Labs Bluetooth Mesh SDK v2.x Quick-Start Guide*.

Use the Bluetooth mesh SDK with the Silicon Labs Simplicity Studio V4 development platform. Simplicity Studio ensures that most software and tool compatibilities are managed correctly. Install software and board firmware updates promptly when you are notified.

Documentation specific to the SDK version is installed with the SDK. Additional information can often be found in the [knowledge base articles \(KBAs\)](#). API references and other information about this and earlier releases is available on <https://docs.silabs.com/>.

7.2 Security Information

Secure Vault Integration

This version of the stack is integrated with Secure Vault Key Management. When deployed to Secure Vault High devices, mesh encryption keys are protected using the Secure Vault Key Management functionality. The table below shows the protected keys and their storage protection characteristics.

Key	Exportability on a node	Exportability on Provisioner	Notes
Network key	Exportable	Exportable	Derivations of the network key exist only in RAM while network keys are stored on flash
Application key	Non-exportable	Exportable	
Device key	Non-exportable	Exportable	In Provisioner's case, applied to Provisioner's own device key as well as other devices' keys

Keys that are marked as "Non-Exportable" can be used but cannot be viewed or shared at runtime.

Keys that are marked as "Exportable" can be used or shared at runtime but remain encrypted while stored in flash.

For more information on Secure Vault Key Management functionality, see [AN1271: Secure Key Storage](#)

Security Advisories

To subscribe to Security Advisories, log in to the Silicon Labs customer portal, then select **Account Home**. Click **HOME** to go to the portal home page and then click the **Manage Notifications** tile. Make sure that 'Software/Security Advisory Notices & Product Change Notices (PCNs)' is checked, and that you are subscribed at minimum for your platform and protocol. Click **Save** to save any changes.

SILICON LABS Search Within the Support Portal for Cases, etc... SEARCH CATHERIN...

HOME CASES SOFTWARE RELEASES

Update Preference

WHAT EMAILS WOULD YOU LIKE TO RECEIVE?

Newsletters

- Community Monthly Newsletter
- Sales Newsletter
- Micrium Newsletter

Product Specific Notifications

- Product Information and Newsletter
- Software/Security Advisory Notices & Product Change Notices (PCNs)
- Technical Document Updates (Release Notes, Data Sheets, etc.)

SELECT THE PRODUCTS TO RECEIVE UPDATES FOR

Select/Unselect All

<input type="checkbox"/> Audio and Radio	<input type="checkbox"/> Power over Ethernet
<input type="checkbox"/> Interface	<input type="checkbox"/> Sensors
<input type="checkbox"/> Isolation	<input type="checkbox"/> TV and Video
<input type="checkbox"/> Modems and DAAs	<input type="checkbox"/> Voice
<input type="checkbox"/> Microcontrollers	<input type="checkbox"/> Wireless
<input type="checkbox"/> 8-bit MCUs <input checked="" type="checkbox"/> 32-bit MCUs	<input type="checkbox"/> Bluetooth Classic <input type="checkbox"/> Bluetooth Low Energy <input checked="" type="checkbox"/> Proprietary
<input type="checkbox"/> Timing	<input type="checkbox"/> Wi-Fi
<input type="checkbox"/> Clocks	<input type="checkbox"/> ZigBee and Thread
<input type="checkbox"/> Buffers	<input type="checkbox"/> Z-Wave
<input type="checkbox"/> Oscillators	
<input type="checkbox"/> CDR and PHY	

7.3 Support

Development Kit customers are eligible for training and technical support. Use the [Silicon Labs Bluetooth mesh web page](#) to obtain information about all Silicon Labs Bluetooth products and services, and to sign up for product support.

Contact Silicon Laboratories support at <http://www.silabs.com/support>.

Simplicity Studio


One-click access to MCU and wireless tools, documentation, software, source code libraries & more. Available for Windows, Mac and Linux!



IoT Portfolio
www.silabs.com/IoT



SW/HW
www.silabs.com/simplicity



Quality
www.silabs.com/quality



Support & Community
www.silabs.com/community

Disclaimer

Silicon Labs intends to provide customers with the latest, accurate, and in-depth documentation of all peripherals and modules available for system and software implementers using or intending to use the Silicon Labs products. Characterization data, available modules and peripherals, memory sizes and memory addresses refer to each specific device, and "Typical" parameters provided can and do vary in different applications. Application examples described herein are for illustrative purposes only. Silicon Labs reserves the right to make changes without further notice to the product information, specifications, and descriptions herein, and does not give warranties as to the accuracy or completeness of the included information. Without prior notification, Silicon Labs may update product firmware during the manufacturing process for security or reliability reasons. Such changes will not alter the specifications or the performance of the product. Silicon Labs shall have no liability for the consequences of use of the information supplied in this document. This document does not imply or expressly grant any license to design or fabricate any integrated circuits. The products are not designed or authorized to be used within any FDA Class III devices, applications for which FDA premarket approval is required or Life Support Systems without the specific written consent of Silicon Labs. A "Life Support System" is any product or system intended to support or sustain life and/or health, which, if it fails, can be reasonably expected to result in significant personal injury or death. Silicon Labs products are not designed or authorized for military applications. Silicon Labs products shall under no circumstances be used in weapons of mass destruction including (but not limited to) nuclear, biological or chemical weapons, or missiles capable of delivering such weapons. Silicon Labs disclaims all express and implied warranties and shall not be responsible or liable for any injuries or damages related to use of a Silicon Labs product in such unauthorized applications.

Note: This content may contain offensive terminology that is now obsolete. Silicon Labs is replacing these terms with inclusive language wherever possible. For more information, visit www.silabs.com/about-us/inclusive-lexicon-project

Trademark Information

Silicon Laboratories Inc.[®], Silicon Laboratories[®], Silicon Labs[®], SiLabs[®] and the Silicon Labs logo[®], Bluegiga[®], Bluegiga Logo[®], Clockbuilder[®], CMEMS[®], DSPLL[®], EFM[®], EFM32[®], EFR[®], Ember[®], Energy Micro, Energy Micro logo and combinations thereof, "the world's most energy friendly microcontrollers", Ember[®], EZLink[®], EZRadio[®], EZRadioPRO[®], Gecko[®], Gecko OS, Gecko OS Studio, ISOModem[®], Precision32[®], ProSLIC[®], Simplicity Studio[®], SiPHY[®], Telegesis, the Telegesis Logo[®], USBXpress[®], Zentri, the Zentri logo and Zentri DMS, Z-Wave[®], and others are trademarks or registered trademarks of Silicon Labs. ARM, CORTEX, Cortex-M3 and THUMB are trademarks or registered trademarks of ARM Holdings. Keil is a registered trademark of ARM Limited. Wi-Fi is a registered trademark of the Wi-Fi Alliance. All other products or brand names mentioned herein are trademarks of their respective holders.



Silicon Laboratories Inc.
400 West Cesar Chavez
Austin, TX 78701
USA

www.silabs.com