



# Silicon Labs OpenThread SDK 2.0.2.0 GA

## Gecko SDK Suite 4.0

### March 9, 2022


Thread is a secure, reliable, scalable, and upgradeable wireless IPv6 mesh networking protocol. It provides low-cost bridging to other IP networks while optimized for low-power / battery-backed operation. The Thread stack is designed specifically for Connected Home applications where IP-based networking is desired and a variety of application layers may be required.

OpenThread released by Google is an open-source implementation of Thread. Google has released OpenThread in order to accelerate the development of products for the connected home and commercial buildings. With a narrow platform abstraction layer and a small memory footprint, OpenThread is highly portable. It supports system-on-chip (SoC), network co-processor (NCP), and radio co-processor (RCP) designs.

Silicon Labs has developed an OpenThread-based SDK tailored to work with Silicon Labs hardware. The Silicon Labs OpenThread SDK is a fully tested enhanced version of the GitHub source. It supports a broader range of hardware than does the GitHub version, and includes documentation and example applications not available on GitHub.

These release notes cover SDK version(s):

- 2.0.2.0 GA released on March 9, 2022
- 2.0.1.0 GA released on January 26, 2022
- 2.0.0.0 GA released on December 15, 2021



**KEY FEATURES**

- EFR32MG24 support
- Multiprotocol and multi-PAN radio coprocessor (RCP) model
- Thread Duckhorn feature support

## Compatibility and Use Notices

For information about security updates and notices, see the Security chapter of the Gecko Platform Release notes installed with this SDK or on the TECH DOCS tab on <https://www.silabs.com/developers/thread>. Silicon Labs also strongly recommends that you subscribe to Security Advisories for up-to-date information. For instructions, or if you are new to the Silicon Labs OpenThread SDK, see [Using This Release](#).

### Compatible Compilers:

GCC (The GNU Compiler Collection) version 10.2.1, provided with Simplicity Studio.

---

## Contents

1	New Items .....	1
1.1	New Components.....	1
1.2	New Features.....	1
2	Improvements.....	2
3	Fixed Issues .....	3
4	Known Issues in the Current Release .....	4
5	Deprecated Items .....	5
6	Removed Items .....	6
7	Multiprotocol Gateway and RCP.....	7
7.1	New Items.....	7
7.2	Improvements .....	7
7.3	Fixed Issues.....	7
7.4	Known Issues in the Current Release .....	7
7.5	Deprecated Items.....	7
7.6	Removed Items.....	7
8	Using This Release .....	8
8.1	Installation and Use.....	8
8.2	OpenThread GitHub Repository.....	8
8.3	OpenThread Border Router GitHub Repository .....	8
8.4	Using the Border Router .....	8
8.5	NCP/RCP Support.....	9
8.6	Security Information .....	9
8.7	Support.....	10

# 1 New Items

## 1.1 New Components

None

## 1.2 New Features

### Added in release 2.0.2.0

The versions of OpenThread and the OpenThread Border Router have been updated. See sections 8.2 and 8.3.

This version of OpenThread includes low-power TCP support. This is not a mandatory Thread 1.3 component, so it is turned off by default in our sample apps.

### Added in release 2.0.1.0

The versions of OpenThread and the OpenThread Border Router have been updated. See sections 8.2 and 8.3.

### Added in release 2.0.0.0

#### **Multiprotocol and multi-PAN radio coprocessor**

This release supports a multiprotocol and multi-PAN radio coprocessor (RCP) model. For more information, see *AN1333: Running Zigbee, OpenThread, and Bluetooth Concurrently on a Linux Host with a Multiprotocol RCP*, provided with the OpenThread and Zigbee SDKs.

#### **Thread Duckhorn Features**

All Thread Duckhorn features in the OpenThread GitHub repo up to and including commit **9dedd1869** and the OpenThread Border Router GitHub repo up to and including commit **58d09bee8** are included and enabled by default.

#### **Documentation**

The following documents have been added:

- AN1372: Configuring OpenThread Applications for Thread 1.3
- AN1333: Running Zigbee, OpenThread, and Bluetooth Concurrently on a Linux Host with a Multiprotocol RCP

## 2 Improvements

None

### 3 Fixed Issues

#### Fixed in release 2.0.2.0

ID #	Description
620720	The 'diag radio state' CLI command used with the Factory Diagnostics Module now operates correctly and no longer just returns 'invalid'.
745530	Fixed Thread 1.1 certification test 5.8.4 with Thread 1.2 Leader DUT fails for missing Discovery Reply.
750315	Fix compilation issue that occurs when FreeRTOS is added to a project.
814247 816037 818555	Fixed 'SL_OPENTHREAD_RTOS_TASK_PRIORITY' undeclared compilation error.
817517	Added the ability to utilize the custom EU164 manufacturing token. To enable, define RADIO_CONFIG_ENABLE_CUSTOM_EUI_SUPPORT.

#### Fixed in release 2.0.1.0

ID #	Description
757778	All OpenThread applications now include the rail_util_rssi component.
759209	Fixed issue where building OpenThread apps on efr32mg2x parts with coexistence enabled gives undeclared identifier error for SL_RAIL_UTIL_COEX_RUNTIME_PHY_SELECT.
764331	For Raspberry Pi and Linux users, please make sure to run "sudo modprobe ip6table_filter" for OTBR firewall support. This allows OTBR scripts to create rules inside the Docker container before otbr-agent starts. This step should be done before starting a docker container.

#### Fixed in release 2.0.0.0

ID #	Description
624220	MBEDTLS_SSL_MAX_CONTENT_LEN needs to be increased to 900 for CoAP.
703615	If the RCP is taken offline, the OTBR doesn't recover.
714451 731194	Issues with promptness and accuracy of enhanced ACKs to CSL children.
730680	Host with CPCd support crashes on cpc read.
752385	OpenThread Sleepy-demo apps that utilize LED and Button ports and pins conflict for 43xx boards

## 4 Known Issues in the Current Release

Issues in bold were added since the previous release. If you have missed a release, recent release notes are available on <https://www.silabs.com/developers/thread> in the Tech Docs tab.

ID #	Description	Workaround
482915 495241	A known limitation with the UART driver can cause characters to be lost on CLI input or output. This can happen during particularly long critical sections that may disable interrupts, so it can be alleviated by repeating the CLI or waiting long enough for state changes.	No known workaround
754514	Double ping reply observed for OTBR ALOC address.	No known workaround
<b>815275</b>	<b>Ability to modify the Radio CCA Modes at compile-time using a configuration option in Simplicity Studio is currently not supported.</b>	<b>Use the SL_OPENTHREAD_RADIO_CCA_MODE configuration option defined in openthread-core-efr32-config.h header file included with your project.</b>

## 5 Deprecated Items

None

## 6 Removed Items

### Removed in release 2.0.0.0

*AN1295: Developing with Thread 1.2* has been removed.



## 7 Multiprotocol Gateway and RCP

### 7.1 New Items

None

### 7.2 Improvements

#### Changed in release 2.0.2.0

The CPC secondary UART driver has been improved to use HW Flow Control.

The default flow control value for *rcp-uart-802154.slcp* and *rcp-uart-802154-blehci.slcp* has been changed to `usartHwFlowControlCtsAndRts`. The default `UART_HARDFLOW` value in *cpcd.conf* has been changed to `true` to match. Silicon Labs recommends use of hard flow control when using CPC over UART.

The CPC daemon can now be configured to restart the secondary in bootloader using pins `nRESET` and `nWAKE`. *cpcd.conf* has been modified; `SPI_WAKE_GPIO` has been removed and replaced by 3 configurations: `BOOTLOADER_RECOVERY_PINS_ENABLED`, `BOOTLOADER_WAKE_GPIO`, and `BOOTLOADER_RESET_GPIO`

### 7.3 Fixed Issues

#### Fixed in release 2.0.2.0

ID #	Description
759772	Fixed an issue in which turning CPCd tracing off caused communication issues between host applications, such as OTBR and zigbee, and the multiprotocol RCP.
759780	Fixed issue where restarting the multi-PAN RCP would cause CPC-enabled host apps such as zigbee, otbr-agent, and ot-cli to disconnect from CPCd.
774747	Fixed a bug in the CPC UART driver that caused OTBR to lose its CPC connection to the multi-PAN RCP, especially at higher baud rates and at startup.
812170	Increased default zigbee table sizes.
813499	Fixed a bug introduced in GSDK 4.0.1 that prevented CPCd from connecting to the multiprotocol RCP ( <i>rcp-uart-802154-blehci</i> and <i>rcp-spi-802154-blehci</i> )
814284	Fixed an issue where the multi-PAN RCP could assert in <code>radioProcessTransmitSecurity</code> under certain circumstances. This was causing intermittent failure of host applications such as OTBR and zigbee.
815222	Zigbee now correctly picks the custom MFG EUI64 if one exists on the chip.
817692	Fixed a zigbee issue in which join attempts were causing an assert on a 64 bit machine (Raspberry Pi OS).

### 7.4 Known Issues in the Current Release

None

### 7.5 Deprecated Items

None

### 7.6 Removed Items

None

## 8 Using This Release

This release contains the following

- Silicon Labs OpenThread stack
- Silicon Labs OpenThread sample applications
- Silicon Labs OpenThread border router

For more information about the OpenThread SDK see [QSG170: Silicon Labs OpenThread QuickStart Guide](#). If you are new to Thread see [UG103.11: Thread Fundamentals](#).

### 8.1 Installation and Use

The OpenThread SDK is part of the Gecko SDK (GSDK), the suite of Silicon Labs SDKs. To quickly get started with OpenThread and the GSDK, start by installing [Simplicity Studio 5](#), which will set up your development environment and walk you through GSDK installation. Simplicity Studio 5 includes everything needed for IoT product development with Silicon Labs devices, including a resource and project launcher, software configuration tools, full IDE with GNU toolchain, and analysis tools. Installation instructions are provided in the online [Simplicity Studio 5 User's Guide](#).

Alternatively, Gecko SDK may be installed manually by downloading or cloning the latest from GitHub. See [https://github.com/SiliconLabs/gecko\\_sdk](https://github.com/SiliconLabs/gecko_sdk) for more information.

The GSDK default installation location has changed with Simplicity Studio 5.3, used with this release.

- Windows: C:\Users\\SimplicityStudio\SDKs\gecko\_sdk
- MacOS: /Users/<NAME>/SimplicityStudio/SDKs/gecko\_sdk

Documentation specific to the SDK version is installed with the SDK. API references and other information about this release are available on <https://docs.silabs.com/openthread/1.2/>.

### 8.2 OpenThread GitHub Repository

The Silicon Labs OpenThread SDK includes all changes from the OpenThread GitHub repo (<https://github.com/openthread/openthread>) up to and including commit **3b79cb0d084**. An enhanced version of the OpenThread repo can be found in the following Simplicity Studio 5 GSDK location:

```
<GSDK Installation Location>\util\third_party\openthread
```

### 8.3 OpenThread Border Router GitHub Repository

The Silicon Labs OpenThread SDK includes all changes from the OpenThread border router GitHub repo (<https://github.com/openthread/ot-br-posix>) up to and including commit **5be35949c6f**. An enhanced version of the OpenThread border router repo can be found in the following Simplicity Studio 5 GSDK location:

```
<GSDK Installation Location>\util\third_party\ot-br-posix
```

### 8.4 Using the Border Router

For ease of use, Silicon Labs recommends the use of a Docker container for your OpenThread border router. Refer to [AN1256: Using the Silicon Labs RCP with the OpenThread Border Router](#) for details on how to set up the correct version of OpenThread border router Docker container. It is available at <https://hub.docker.com/r/siliconlabsinc/openthread-border-router>.

If you are manually installing a border router, using the copies provided with the Silicon Labs OpenThread SDK, refer to [AN1256: Using the Silicon Labs RCP with the OpenThread Border Router](#) for more details.

Although updating the border router environment to a later GitHub version is supported on the OpenThread website, it may make the border router incompatible with the OpenThread RCP stack in the SDK.

## 8.5 NCP/RCP Support

The OpenThread NCP support is included with OpenThread SDK but any use of this support should be considered experimental. The OpenThread RCP is fully implemented and supported.

## 8.6 Security Information

### Secure Vault Integration

When deployed to Secure Vault High devices, sensitive keys are protected using the Secure Vault Key Management functionality. The following table shows the protected keys and their storage protection characteristics.

Wrapped Key	Exportable / Non-Exportable	Notes
Thread Master Key	Exportable	Must be exportable to form the TLVs
PSKc	Exportable	Must be exportable to form the TLVs
Key Encryption Key	Exportable	Must be exportable to form the TLVs
MLE Key	Non-Exportable	
Temporary MLE Key	Non-Exportable	
MAC Previous Key	Non-Exportable	
MAC Current Key	Non-Exportable	
MAC Next Key	Non-Exportable	

Wrapped keys that are marked as “Non-Exportable” can be used but cannot be viewed or shared at runtime.

Wrapped keys that are marked as “Exportable” can be used or shared at runtime but remain encrypted while stored in flash.

For more information on Secure Vault Key Management functionality, see [AN1271: Secure Key Storage](#).

### Security Advisories

To subscribe to Security Advisories, log in to the Silicon Labs customer portal, then select **Account Home**. Click **HOME** to go to the portal home page and then click the **Manage Notifications** tile. Make sure that ‘Software/Security Advisory Notices & Product Change Notices (PCNs)’ is checked, and that you are subscribed at minimum for your platform and protocol. Click **Save** to save any changes.

**Update Preference**

WHAT EMAILS WOULD YOU LIKE TO RECEIVE?

Newsletters

- Community Monthly Newsletter
- Sales Newsletter
- Micrium Newsletter

Product Specific Notifications

- Product Information and Newsletter
- Software/Security Advisory Notices & Product Change Notices (PCNs)
- Technical Document Updates (Release Notes, Data Sheets, etc.)

SELECT THE PRODUCTS TO RECEIVE UPDATES FOR

Select/Unselect All

<input type="checkbox"/> Audio and Radio	<input type="checkbox"/> Power over Ethernet
<input type="checkbox"/> Interface	<input type="checkbox"/> Sensors
<input type="checkbox"/> Isolation	<input type="checkbox"/> TV and Video
<input type="checkbox"/> Modems and DAAs	<input type="checkbox"/> Voice
<input type="checkbox"/> Microcontrollers	<input type="checkbox"/> Wireless
<input type="checkbox"/> 8-bit MCUs	<input type="checkbox"/> Bluetooth Classic
<input checked="" type="checkbox"/> 32-bit MCUs	<input type="checkbox"/> Bluetooth Low Energy
<input type="checkbox"/> Timing	<input checked="" type="checkbox"/> Proprietary
<input type="checkbox"/> Clocks	<input type="checkbox"/> Wi-Fi
<input type="checkbox"/> Buffers	<input type="checkbox"/> ZigBee and Thread
<input type="checkbox"/> Oscillators	<input type="checkbox"/> Z-Wave
<input type="checkbox"/> CDR and PHY	

## 8.7 Support

Development Kit customers are eligible for training and technical support. Use the [Silicon Laboratories Thread web page](#) to obtain information about all Silicon Labs OpenThread products and services, and to sign up for product support.

You can contact Silicon Laboratories support at <http://www.silabs.com/support>.

# Simplicity Studio

One-click access to MCU and wireless tools, documentation, software, source code libraries & more. Available for Windows, Mac and Linux!



**IoT Portfolio**  
[www.silabs.com/IoT](http://www.silabs.com/IoT)



**SW/HW**  
[www.silabs.com/simplicity](http://www.silabs.com/simplicity)



**Quality**  
[www.silabs.com/quality](http://www.silabs.com/quality)



**Support & Community**  
[www.silabs.com/community](http://www.silabs.com/community)

## Disclaimer

Silicon Labs intends to provide customers with the latest, accurate, and in-depth documentation of all peripherals and modules available for system and software implementers using or intending to use the Silicon Labs products. Characterization data, available modules and peripherals, memory sizes and memory addresses refer to each specific device, and "Typical" parameters provided can and do vary in different applications. Application examples described herein are for illustrative purposes only. Silicon Labs reserves the right to make changes without further notice to the product information, specifications, and descriptions herein, and does not give warranties as to the accuracy or completeness of the included information. Without prior notification, Silicon Labs may update product firmware during the manufacturing process for security or reliability reasons. Such changes will not alter the specifications or the performance of the product. Silicon Labs shall have no liability for the consequences of use of the information supplied in this document. This document does not imply or expressly grant any license to design or fabricate any integrated circuits. The products are not designed or authorized to be used within any FDA Class III devices, applications for which FDA premarket approval is required or Life Support Systems without the specific written consent of Silicon Labs. A "Life Support System" is any product or system intended to support or sustain life and/or health, which, if it fails, can be reasonably expected to result in significant personal injury or death. Silicon Labs products are not designed or authorized for military applications. Silicon Labs products shall under no circumstances be used in weapons of mass destruction including (but not limited to) nuclear, biological or chemical weapons, or missiles capable of delivering such weapons. Silicon Labs disclaims all express and implied warranties and shall not be responsible or liable for any injuries or damages related to use of a Silicon Labs product in such unauthorized applications.

**Note: This content may contain offensive terminology that is now obsolete. Silicon Labs is replacing these terms with inclusive language wherever possible. For more information, visit [www.silabs.com/about-us/inclusive-lexicon-project](http://www.silabs.com/about-us/inclusive-lexicon-project)**

## Trademark Information

Silicon Laboratories Inc.<sup>®</sup>, Silicon Laboratories<sup>®</sup>, Silicon Labs<sup>®</sup>, SiLabs<sup>®</sup> and the Silicon Labs logo<sup>®</sup>, Bluegiga<sup>®</sup>, Bluegiga Logo<sup>®</sup>, EFM<sup>®</sup>, EFM32<sup>®</sup>, EFR, Ember<sup>®</sup>, Energy Micro, Energy Micro logo and combinations thereof, "the world's most energy friendly microcontrollers", Redpine Signals<sup>®</sup>, WiSeConnect, n-Link, ThreadArch<sup>®</sup>, EZLink<sup>®</sup>, EZRadio<sup>®</sup>, EZRadioPRO<sup>®</sup>, Gecko<sup>®</sup>, Gecko OS, Gecko OS Studio, Precision32<sup>®</sup>, Simplicity Studio<sup>®</sup>, Telegesis, the Telegesis Logo<sup>®</sup>, USBXpress<sup>®</sup>, Zentri, the Zentri logo and Zentri DMS, Z-Wave<sup>®</sup>, and others are trademarks or registered trademarks of Silicon Labs. ARM, CORTEX, Cortex-M3 and THUMB are trademarks or registered trademarks of ARM Holdings. Keil is a registered trademark of ARM Limited. Wi-Fi is a registered trademark of the Wi-Fi Alliance. All other products or brand names mentioned herein are trademarks of their respective holders.



Silicon Laboratories Inc.  
400 West Cesar Chavez  
Austin, TX 78701  
USA

[www.silabs.com](http://www.silabs.com)