



Wi-SUN SDK 1.4.0.0 GA

Gecko SDK Suite 4.2

December 14, 2022

Wireless Smart Ubiquitous Network (Wi-SUN) is the leading IPv6 sub-GHz mesh technology for smart city and smart utility applications. Wi-SUN brings Smart Ubiquitous Networks to service providers, utilities, municipalities/local government, and other enterprises, by enabling interoperable, multi-service, and secure wireless mesh networks. Wi-SUN can be used for large-scale outdoor IoT wireless communication networks in a wide range of applications covering both line-powered and battery-powered nodes.

Silicon Labs' Wi-SUN hardware is certified by the Wi-SUN Alliance, a global industry association devoted to seamless LPWAN connectivity. Wi-SUN builds upon open standard internet protocols (IP) and APIs, enabling developers to extend existing infrastructure platforms to add new capabilities. Built to scale with long-range capabilities, high-data throughput and IPv6 support, Wi-SUN simplifies wireless infrastructure for industrial applications and the evolution of smart cities.

These release notes cover SDK versions:

1.4.0.0 released December 14, 2022



KEY FEATURES

Wi-SUN Stack

- Added minimal support for FAN1.1 LFN (Limited Functional Node), including an API to configure the device role, and a new set of libraries supporting both LFN and FFN device types.
- Added support for FAN 1.1 PHY mode switch.
- Added support for FSK FEC.
- Added support for EFR32FG25. It supports all FAN1.1 OFDM modulation schemes and all FAN1.0 FSK configurations.
- Added support for EFF01.

Wi-SUN Applications

- Added support for EFR32FG25.
- Added FAN 1.1 PHY support (settings and CLI).
- Added a CoAP Advanced Resource Handler.
- Added support for iPerf multicast.
- Added support for CPC in Wi-SUN RCP.

Compatibility and Use Notices

For information about security updates and notices, see the Security chapter of the Gecko Platform Release notes installed with this SDK or on the TECH DOCS tab on <https://www.silabs.com/developers/wi-sun-protocol-stack>. Silicon Labs also strongly recommends that you subscribe to Security Advisories for up-to-date information. For instructions, or if you are new to the Silicon Labs Wi-SUN SDK, see [Using This Release](#).

Compatible Compilers:

IAR Embedded Workbench for ARM (IAR-EWARM) version 9.20.4

- Using wine to build with the IarBuild.exe command line utility or IAR Embedded Workbench GUI on macOS or Linux could result in incorrect files being used due to collisions in wine's hashing algorithm for generating short file names.
- Customers on macOS or Linux are advised not to build with IAR outside of Simplicity Studio. Customers who do should carefully verify that the correct files are being used.

GCC (The GNU Compiler Collection) version 10.3-2021.10, provided with Simplicity Studio.

Contents

- 1 Wi-SUN Stack.....2
 - 1.1 New Items.....2
 - 1.2 Improvements.....2
 - 1.3 Fixed Issues.....2
 - 1.4 Known Issues in the Current Release.....2
 - 1.5 Deprecated Items.....3
 - 1.6 Removed Items.....3
- 2 Wi-SUN Applications.....4
 - 2.1 New Items.....4
 - 2.2 Improvements.....4
 - 2.3 Fixed Issues.....4
 - 2.4 Known Issues in the Current Release.....4
 - 2.5 Deprecated Items.....4
 - 2.6 Removed Items.....5
- 3 Using This Release.....6
 - 3.1 Installation and Use.....6
 - 3.2 Security Information.....6
 - 3.3 Support.....7

1 Wi-SUN Stack

1.1 New Items

Added in release 1.4.0.0

- Added minimal support for FAN1.1 LFN (Limited Functional Node). LFN devices are able to connect and communicate but are not using any of the EFR32 energy management mode. As such, they are not optimized for battery powered devices and should only be used for evaluation and experimentation.
- Added a new API `sl_wisun_set_device_type()` that configures the role of device. It can be either a router (FFN – Full Functional Node) or an end node (LFN)
- Added a new set of libraries supporting both LFN and FFN device types. Those libraries are used when the new “Stack LFN Support” plugin is installed.
- Added support for FAN 1.1 PHY mode switch.
 - Added a new API `sl_wisun_set_mode_switch()` that indicates if the device can mode switch with a given neighbor.
 - Added new APIs `sl_wisun_set_pom_ie()` and `sl_wisun_get_pom_ie()` that write or read the content of the POM-IE (PHY Operating Mode Information Element). It contains the list of the PHY operating mode a node is willing to use for communication.
- Added a new API `sl_wisun_join()` that triggers a new connection. It can be used either with the old (1V08 – regulatory domain, operating class, operating mode) or the new (1VA8 – regulatory domain, channel plan id, PHY mode if) nomenclature. That new API is meant to replace `sl_wisun_connect()`.
- Added a new API `sl_wisun_set_connection_parameters()` that extends the set of the configuration parameters. Used in pair with `sl_wisun_join()`, it replaces `sl_wisun_connect()` network size parameter.
- Added support for FSK FEC. FEC can be enable either by setting `fec` field of `sl_wisun_phy_config_t` structure or by using a PHY mode id that explicitly enables FEC.
- Added support of EFR32FG25. It supports all FAN1.1 OFDM modulation schemes and all FAN1.0 FSK configurations.
- Added support of EFF01

1.2 Improvements

None

1.3 Fixed Issues

None

1.4 Known Issues in the Current Release

ID #	Description	Workaround
1078454	The wrong radio entry can be used if a radio configuration file contains the same PHY more than once. It will always select the first entry found that matches the PHY charatersitcs. It can cause a single PHY to be selected instead of a multi-PHY and make the use of mode switch impossible.	Start the radio configuration files with the multi-PHY.
1059919	A wrong RSSI estimation leads an imprecise RSL computation. It can trigger to a suboptimal parent selection on heterogeneous networks.	

1.5 Deprecated Items

Deprecated in release 1.4.0.0

- `sl_wisun_connect()` is replaced by `sl_wisun_join()`.
- `sl_wisun_set_channel_plan()` is replaced by `sl_wisun_join()`.
- `sl_wisun_set_network_size()` is replaced by `sl_wisun_set_connection_parameters()`

1.6 Removed Items

None

2 Wi-SUN Applications

2.1 New Items

Added in release 1.4.0.0

- Added support of EFR32FG25
- FAN 1.1 PHY support (settings and CLI)
- CoAP Advanced Resource Handler
- Added support of CPC in Wi-SUN RCP

2.2 Improvements

Added in release 1.4.0.0

- iPerf Improvements
 - CLI component is separated
 - Multicast support
- CoAP Improvements
 - Resource Discovery Query Improvement
 - Extended resource support (CoAP Meter update also)
- Network Measurement Application Improvements
 - Multicast support for ping and iPerf
 - Remote CLI control over CoAP
 - LCD GUI improvements
 - PHY selection
 - iPerf test visualization
 - GUI refactor
- Wi-SUN Configurator
 - FAN1.1 PHY support beside FAN1.0
 - Default PHY Selection
- Refactor memory management (Os objects and their allocations are organized into heap)

2.3 Fixed Issues

None

2.4 Known Issues in the Current Release

Issues in bold were added since the previous release.

ID #	Description	Workaround
	Simplicity Studio – Network Analyzer: Wi-SUN Encrypted Packets are not supported.	

2.5 Deprecated Items

None

2.6 Removed Items

None

3 Using This Release

This release contains the following

- Wi-SUN stack library
- Wi-SUN sample applications
- Wi-SUN border router pre-compiled demos
- Documentation

If you are a first time user, see *QSG181: Silicon Labs Wi-SUN Quick-Start Guide*.

3.1 Installation and Use

The Wi-SUN SDK is provided as part of the Gecko SDK (GSDK), the suite of Silicon Labs SDKs. To quickly get started with the GSDK, install [Simplicity Studio 5](#), which will set up your development environment and walk you through GSDK installation. Simplicity Studio 5 includes everything needed for IoT product development with Silicon Labs devices, including a resource and project launcher, software configuration tools, full IDE with GNU toolchain, and analysis tools. Installation instructions are provided in the online [Simplicity Studio 5 User's Guide](#).

Alternatively, Gecko SDK may be installed manually by downloading or cloning the latest from GitHub. See https://github.com/SiliconLabs/gecko_sdk for more information.

Simplicity Studio installs the GSDK by default in:

- (Windows): C:\Users\<<NAME>\SimplicityStudio\SDKs\gecko_sdk
- (MacOS): /Users/<NAME>/SimplicityStudio/SDKs/gecko_sdk

Documentation specific to the SDK version is installed with the SDK.

3.2 Security Information

Secure Vault Integration

This version of the stack does not integrate Secure Vault Key Management.

Security Advisories

To subscribe to Security Advisories, log in to the Silicon Labs customer portal, then select **Account Home**. Click **HOME** to go to the portal home page and then click the **Manage Notifications** tile. Make sure that 'Software/Security Advisory Notices & Product Change Notices (PCNs)' is checked, and that you are subscribed at minimum for your platform and protocol. Click **Save** to save any changes.

SILICON LABS Search Within the Support Portal for Cases, etc... SEARCH CATHERIN...

HOME CASES SOFTWARE RELEASES

Update Preference

WHAT EMAILS WOULD YOU LIKE TO RECEIVE?

Newsletters

- Community Monthly Newsletter
- Sales Newsletter
- Micrium Newsletter

Product Specific Notifications

- Product Information and Newsletter
- Software/Security Advisory Notices & Product Change Notices (PCNs)
- Technical Document Updates (Release Notes, Data Sheets, etc.)

SELECT THE PRODUCTS TO RECEIVE UPDATES FOR

Select/Unselect All

<input type="checkbox"/> Audio and Radio	<input type="checkbox"/> Power over Ethernet
<input type="checkbox"/> Interface	<input type="checkbox"/> Sensors
<input type="checkbox"/> Isolation	<input type="checkbox"/> TV and Video
<input type="checkbox"/> Modems and DAAs	<input type="checkbox"/> Voice
<input type="checkbox"/> Microcontrollers	<input type="checkbox"/> Wireless
<input type="checkbox"/> 8-bit MCUs	<input type="checkbox"/> Bluetooth Classic
<input checked="" type="checkbox"/> 32-bit MCUs	<input type="checkbox"/> Bluetooth Low Energy
<input type="checkbox"/> Timing	<input checked="" type="checkbox"/> Proprietary
<input type="checkbox"/> Clocks	<input type="checkbox"/> Wi-Fi
<input type="checkbox"/> Buffers	<input type="checkbox"/> ZigBee and Thread
<input type="checkbox"/> Oscillators	<input type="checkbox"/> Z-Wave
<input type="checkbox"/> CDR and PHY	

3.3 Support

Development Kit customers are eligible for training and technical support. Contact Silicon Laboratories support at <http://www.silabs.com/support>.

Simplicity Studio

One-click access to MCU and wireless tools, documentation, software, source code libraries & more. Available for Windows, Mac and Linux!



IoT Portfolio
www.silabs.com/IoT



SW/HW
www.silabs.com/simplicity



Quality
www.silabs.com/quality



Support & Community
www.silabs.com/community

Disclaimer

Silicon Labs intends to provide customers with the latest, accurate, and in-depth documentation of all peripherals and modules available for system and software implementers using or intending to use the Silicon Labs products. Characterization data, available modules and peripherals, memory sizes and memory addresses refer to each specific device, and "Typical" parameters provided can and do vary in different applications. Application examples described herein are for illustrative purposes only. Silicon Labs reserves the right to make changes without further notice to the product information, specifications, and descriptions herein, and does not give warranties as to the accuracy or completeness of the included information. Without prior notification, Silicon Labs may update product firmware during the manufacturing process for security or reliability reasons. Such changes will not alter the specifications or the performance of the product. Silicon Labs shall have no liability for the consequences of use of the information supplied in this document. This document does not imply or expressly grant any license to design or fabricate any integrated circuits. The products are not designed or authorized to be used within any FDA Class III devices, applications for which FDA premarket approval is required or Life Support Systems without the specific written consent of Silicon Labs. A "Life Support System" is any product or system intended to support or sustain life and/or health, which, if it fails, can be reasonably expected to result in significant personal injury or death. Silicon Labs products are not designed or authorized for military applications. Silicon Labs products shall under no circumstances be used in weapons of mass destruction including (but not limited to) nuclear, biological or chemical weapons, or missiles capable of delivering such weapons. Silicon Labs disclaims all express and implied warranties and shall not be responsible or liable for any injuries or damages related to use of a Silicon Labs product in such unauthorized applications.

Note: This content may contain offensive terminology that is now obsolete. Silicon Labs is replacing these terms with inclusive language wherever possible. For more information, visit www.silabs.com/about-us/inclusive-lexicon-project

Trademark Information

Silicon Laboratories Inc.[®], Silicon Laboratories[®], Silicon Labs[®], SiLabs[®] and the Silicon Labs logo[®], Bluegiga[®], Bluegiga Logo[®], EFM[®], EFM32[®], EFR, Ember[®], Energy Micro, Energy Micro logo and combinations thereof, "the world's most energy friendly microcontrollers", Redpine Signals[®], WiSeConnect, n-Link, ThreadArch[®], EZLink[®], EZRadio[®], EZRadioPRO[®], Gecko[®], Gecko OS, Gecko OS Studio, Precision32[®], Simplicity Studio[®], Telegesis, the Telegesis Logo[®], USBXpress[®], Zentri, the Zentri logo and Zentri DMS, Z-Wave[®], and others are trademarks or registered trademarks of Silicon Labs. ARM, CORTEX, Cortex-M3 and THUMB are trademarks or registered trademarks of ARM Holdings. Keil is a registered trademark of ARM Limited. Wi-Fi is a registered trademark of the Wi-Fi Alliance. All other products or brand names mentioned herein are trademarks of their respective holders.



Silicon Laboratories Inc.
400 West Cesar Chavez
Austin, TX 78701
USA

www.silabs.com