



Silicon Labs *Bluetooth*[®] SDK 2.12.0.0 GA

19Q2 Gecko SDK

June 7, 2019

Silicon Labs is a leading vendor in Bluetooth hardware and software technologies, used in products such as sports and fitness, consumer electronics, beacons, and smart home applications. The core SDK is an advanced Bluetooth 5-compliant stack that provides all of the core functionality along with multiple API to simplify development. The core functionality offers both standalone mode allowing a developer to create and run their application directly on the SoC, or in NCP mode allowing for the use of an external host MCU.

Extensions to the SDK, include Bluetooth Mesh and Homekit for customers seeking the additional capabilities.

These release notes cover SDK version:

2.12.0.0 released on June 7, 2019



KEY FEATURES

- Added support for new parts
 - EFR32[B|M]G13 Rev D
 - EFR32BG12 QFN68 I-Grade
- Bluetooth 5.0: Advertising packet chaining
- Selected quality improvements and bug fixes

Compatibility and Use Notices

If you are new to the Silicon Labs Bluetooth SDK, see [Using This Release](#).

Compatible Compilers:

IAR Embedded Workbench for ARM (IAR-EWARM) version 8.30.1

- Using wine to build with the `IarBuild.exe` command line utility or IAR Embedded Workbench GUI on macOS or Linux could result in incorrect files being used due to collisions in wine's hashing algorithm for generating short file names.
- Customers on macOS or Linux are advised not to build with IAR outside of Simplicity Studio. Customers who do should carefully verify that the correct files are being used.

GCC (The GNU Compiler Collection) version 7.2.1, provided with Simplicity Studio.

Contents

- 1 New Items 3
 - 1.1 New Features 3
 - 1.2 New APIs 3
- 2 Improvements 4
 - 2.1 Changed APIs 4
- 3 Fixed Issues 5
- 4 Known Issues in the Current Release 6
- 5 Deprecated Items 7
- 6 Removed Items 8
- 7 Using This Release 9
 - 7.1 Installation and Use 9
 - 7.2 Support 9
- 8 Legal 10
 - 8.1 Disclaimer 10
 - 8.2 Trademark Information 10

1 New Items

Gecko Platform release notes are now available through Simplicity Studio's Launcher Perspective, under **SDK Documentation > Bluetooth SDK 2.12.n.n > Release Notes**. The Gecko Platform code provides functionality that supports protocol plugins and APIs in the form of drivers and other lower layer features that interact directly with Silicon Labs chips and modules. Gecko Platform components include EMLIB, EMDRV, RAIL Library, NVM3, and mbedTLS.

1.1 New Features

Added in release 2.12.0.0

Advertising packet chaining

With this feature, the total amount of advertising data in an advertising packet can be up to 1650 bytes in extended advertising.

1.2 New APIs

For additional documentation and command descriptions please refer to the [Bluetooth Software API Reference Manual](#).

Added in release 2.12.0.0

cmd_gatt_server_set_max_mtu

cmd_le_connection_set_timing_parameters

cmd_le_gap_set_conn_timing_parameters

cmd_le_gap_set_long_advertising_data

cmd_sm_set_minimum_key_size

cmd_system_data_buffer_write

cmd_system_data_buffer_clear

2 Improvements

2.1 Changed APIs

Changed in release 2.12.0.0

cmd_le_gap_bt5_set_adv_data

Removed the 191 bytes advertising data limitation for extended advertising.

cmd_le_gap_set_adv_data

Removed the 191 bytes advertising data limitation for extended advertising.

evt_le_gap_extended_scan_response

Added new value in packet_type parameter for data incomplete status.

evt_le_gap_scan_response

Added new value in packet_type parameter for data incomplete status.

evt_sync_data

Added new value in data_status parameter for data incomplete status.

3 Fixed Issues

Fixed in release 2.12.0.0

ID #	Description
3414	In Bluetooth SDK 2.11.4 and 2.11.5, occasionally the stack is unable to receive all GATT write without response or characteristic value notification PDUs.
4559	Deleting the bonding of a device while the device is still connected causes the stack using outdated bonding data on the connection. This has been fixed so that the connection is also closed after the bonding has been deleted.
5940	The application cannot configure the maximum ATT MTU if GATT client is excluded. This has been fixed by adding a new equivalent API in GATT server class.
6051	When Bluetooth runs in RTOS, the stack initialization may cause assertions.
6135	Advertising could not be restarted if a timeout has been set previously.
6189	Increasing security on a connection with previously bonded devices may fail.
6279	The stack does not correctly inform the application about ATT MTU size change if the remote device first denies the stack's ATT MTU exchange request and then initiates another ATT MTU exchange request.

4 Known Issues in the Current Release

Issues in bold were added since the previous release.

ID #	Description	Workaround
1835	With certain events, GCC breakpoints cannot be set.	Change optimization level to none in project settings
4521	Command <code>gecko_cmd_gatt_discover_primary_services_by_uuid</code> returns success in case of incomplete parameters.	None
5390	The <code>sync_data</code> event does not report TX power.	None

5 Deprecated Items

Deprecated in release 2.12.0.0

As of June 2019 Simplicity Studio 3.0 is being deprecated. All access will be removed from Silicon Labs' website at the end of 2019.

Deprecated APIs

cmd_le_gap_set_conn_parameters

The replacement is cmd_le_gap_set_conn_timing_parameters.

cmd_le_connection_set_parameters

The replacement is cmd_le_connection_set_timing_parameters.

6 Removed Items

Removed in release 2.12.0.0

None

7 Using This Release

This release contains the following

- Silicon Labs Bluetooth stack library
- Bluetooth sample applications

For more information about the Bluetooth SDK see [QSG139: Getting Started with Bluetooth® Software Development](#). If you are new to Bluetooth see [UG103.14: Bluetooth LE Fundamentals](#).

7.1 Installation and Use

A registered account at Silicon Labs is required in order to download the Silicon Labs Bluetooth SDK. You can register at https://siliconlabs.force.com/apex/SL_CommunitiesSelfReg?form=short.

Stack installation instructions are covered in [QSG139: Getting Started with Bluetooth® Software Development](#).

Use the Bluetooth SDK with the Silicon Labs Simplicity Studio V4 development platform. Simplicity Studio ensures that most software and tool compatibilities are managed correctly. Install software and board firmware updates promptly when you are notified.

Documentation specific to the SDK version is installed with the SDK. Additional information can often be found in the [knowledge base articles \(KBAs\)](#). API references and other information about this and earlier releases is available on <https://docs.silabs.com/>.

7.2 Support

Development Kit customers are eligible for training and technical support. You can use the [Silicon Labs Bluetooth LE web page](#) to obtain information about all Silicon Labs Bluetooth products and services, and to sign up for product support.

You can contact Silicon Laboratories support at <http://www.silabs.com/support>.

8 Legal

8.1 Disclaimer

Silicon Labs intends to provide customers with the latest, accurate, and in-depth documentation of all peripherals and modules available for system and software implementers using or intending to use the Silicon Labs products. Characterization data, available modules and peripherals, memory sizes and memory addresses refer to each specific device, and "Typical" parameters provided can and do vary in different applications.

Application examples described herein are for illustrative purposes only.

Silicon Labs reserves the right to make changes without further notice and limitation to product information, specifications, and descriptions herein, and does not give warranties as to the accuracy or completeness of the included information. Silicon Labs shall have no liability for the consequences of use of the information supplied herein. This document does not imply or express copyright licenses granted hereunder to design or fabricate any integrated circuits. The products are not designed or authorized to be used within any Life Support System. A "Life Support System" is any product or system intended to support or sustain life and/or health, which, if it fails, can be reasonably expected to result in significant personal injury or death. Silicon Labs products are not designed or authorized for military applications. Silicon Labs products shall under no circumstances be used in weapons of mass destruction including (but not limited to) nuclear, biological or chemical weapons, or missiles capable of delivering such weapons.

8.2 Trademark Information

Silicon Laboratories Inc.®, Silicon Laboratories®, Silicon Labs®, SiLabs® and the Silicon Labs logo®, Bluegiga®, Bluegiga Logo®, Clockbuilder®, CMEMS®, DSPLL®, EFM®, EFM32®, EFR, Ember®, Energy Micro, Energy Micro logo and combinations thereof, "the world's most energy friendly microcontrollers", Ember®, EZLink®, EZRadio®, EZRadioPRO®, Gecko®, ISOModem®, Micrium, Precision32®, ProSLIC®, Simplicity Studio®, SiPHY®, Telegesis, the Telegesis Logo®, USBXpress®, Zentri, Z-Wave and others are trademarks or registered trademarks of Silicon Labs.

ARM, CORTEX, Cortex-M3 and THUMB are trademarks or registered trademarks of ARM Holdings.

Keil is a registered trademark of ARM Limited. All other products or brand names mentioned herein are trademarks of their respective holders.